AddOn Computer 34A Mauchly Irvine, Ca 92618

Office: 949.861.2800 Fax: 949.861.2812 www.addoncomputer.com

POCOON MEDIA CONVERTERS - MEMORY UPGRADES

BATTERIES - NETWORKING TRANSCEIVERS

16 Slot Rack Mountable

100BASE-10GBASE MCC Media Converter Chasis, Media Converter Cards



Features

Interface/Ports: 1 x RJ-45, 1 X SC, ST, SFP, SFP+, XFP

Connectivity: Twisted Pair, Fiber

Connectivity Media: 10/100Base-TX Twisted Pair

100Base-FX (50/125 μ m, 62.5/125 μ m MMF)

 $(9/125 \, \mu \text{m SMF})$

1000Base-XX, 10GBase

Distance Supported: 550m, 2km, 20km Wavelength: 1310nm, 1550nm

Network Technology: 10/100Base-TX, 100Base-FX, 1000Base-XX

Status Indicators: Power

Copper Link Fiber Link

Copper Receive activity Fiber Receive activity

Input Voltage: 120\

Input Current: Chasis: 16A, Card: 750mA Temperature: $32^{\circ}F$ (0°C) ~ $122^{\circ}F$ (50°C) Humidity: $5 \sim 90\%$ Non-condensing

Product Description

The 16 Slot Racks are 19" rack mountable 10/100/1000M fiber media converter. Offering a great space/performance ratio, the 16 Slot Racks covers various fiber media converter functions including variety of data rate, SM/MM, single fiber and double fiber with simple setup. The ADD-MRACK-16 and ADD-MRACK-16 are standard with Dual redundant power supply.

AddOn Media Network Interface Cards are 100% compliant for all of your networking needs. Media Converter Cards provides a 10/100/1000M Base-TX to 1000Base-XX MMF and SMF fiber port. Economically priced.

ADD-RACK-16

Media Converter Chasis 19"
16-Slot Dual-Power Rack Mount

ADD-MRACK-16

Managed Media Converter Chasis 19" 16-Slot Dual-Power Rack Mount

ADD-MCC1MMM2K

Media Converter Card 100FX 10/100M 1310NM MMF SC 2km Reach

ADD-MCC1MSM20

Media Converter Card 100LX 10/100M 1310NM SMF 20km Reach

ADD-MCC1MBX53

Media Converter Card 100BXD 1550/1310NM SMF SC BiDi 20km Reach

ADD-MCC1GMM5M

Media Converter Card 1000BSX 10/100/1000M 850NM MMF SC 550m

ADD-MCC1GSM20

Media Converter Card 1000BLX 10/100/1000M 1310NM SMF SC 20km

ADD-MCCTXSFP*

Media Converter Card 1000BT-SPF 10/100/1000M with Open SFP Slot

ADD-MCC10G2SFP*

Media Converter Card 10G OEO Converter 2 Open SFP+ Slots

ADD-MCC10GXSFP*

Media Converter Card 10G OEO Converter SFP+ and XFP Slot

ADD-MCC10G2XFP*

Media Converter Card 10G OEO Converter 2 Open XFP Slots

ADD-MCC4G2SFP*

Media Converter Card 125M to 4G OEO Converter 2 Open SFP Slots

^{*}For complete list of SFP/XFP module please visit www.addoncomputer.com